



## TP Link TD-8151N



**Primo Telecommunication**

072-2467000 | [support@099.net.i](mailto:support@099.net.i) | [www.099.net.il](http://www.099.net.il)

## Step 1: **Connect to the Router**

To access the web user interface, open a web-browser such as Internet Explorer and enter the IP address of the router (**10.0.0.138**) into the address bar and press the Enter key on your keyboard



**Username:** admin

**Password:** admin





In The Next Windows, Click on **Interface Setup** and below select Internet and continue to the following settings

**TP-LINK®** 150Mbps Wireless N ADSL2+ Modem Router

Quick Start **Interface Setup** Advanced Setup Access Management Maintenance Status Help

Internet LAN Wireless

**ATM VC**

Virtual Circuit: PVC 5 PVCs Summary

Status:  Activated  Deactivated

VPI: 8 (range: 0~255)

VCI: 48 (range: 1~65535)

**QoS**

ATM QoS: UBR

PCR: 0 cells/second

SCR: 0 cells/second

MBS: 0 cells

**Encapsulation**

ISP:  Dynamic IP Address  
 Static IP Address  
 PPPoA/PPPoE  
 Bridge Mode

**PPPoE/PPPoA**

Servicename:

Username: user@099

Password: \*\*\*\*

Encapsulation: PPPoE LLC

Bridge Interface:  Activated  Deactivated

**Connection Setting**



**Primo Telecommunication**

072-2467000 | support@099.net.i | www.099.net.il



VPI : 8  
VCI : 48  
ATM QoS UBR .  
ISP: PPPoA / PPPoE

Then Fill In Your **Username** And **Password**.

Connection Setting	Bridge Interface : <input type="radio"/> Activated <input checked="" type="radio"/> Deactivated
	Connection : <input checked="" type="radio"/> Always On (Recommended) <input type="radio"/> Connect On-Demand (Close if idle for <input type="text" value="0"/> minutes) <input type="radio"/> Connect Manually
IP Address	TCP MSS Option : TCP MSS(default:1400) <input type="text" value="1400"/> bytes
	Get IP Address : <input type="radio"/> Static <input checked="" type="radio"/> Dynamic
	Static IP Address : <input type="text" value="0.0.0.0"/>
	IP Subnet Mask : <input type="text" value="0.0.0.0"/>
	Gateway : <input type="text" value="0.0.0.0"/>
	NAT : Enable ▾
	Default Route : <input checked="" type="radio"/> Yes <input type="radio"/> No
	TCP MTU Option : TCP MTU(default:1480) <input type="text" value="1480"/> bytes
Dynamic Route : RP2-B ▾ Direction : Both ▾	
Multicast : Disabled ▾	
<input type="button" value="SAVE"/> <input type="button" value="DELETE"/>	



**Primo Telecommunication**

072-2467000 | support@099.net.i | www.099.net.il