



TP Link TD-W8901G



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il

Step 1: **Connect to the Router**

To access the web user interface, open a web-browser such as Internet Explorer and enter the IP address of the router (**10.0.0.138**) into the address bar and press the Enter key on your keyboard



Username: admin

Password: admin





In The Next Windows, Click on **Interface Setup** and below select Internet and continue to the following settings

TP-LINK® 150Mbps Wireless N ADSL2+ Modem Router

Interface | Quick Start | **Interface Setup** | Advanced Setup | Access Management | Maintenance | Status | Help

Internet | LAN | Wireless

ATM VC

Virtual Circuit: PVC 5 | PVCs Summary

Status: Activated Deactivated

VPI: 8 (range: 0~255)

VCI: 48 (range: 1~65535)

QoS

ATM QoS: UBR

PCR: 0 cells/second

SCR: 0 cells/second

MBS: 0 cells

Encapsulation

ISP: Dynamic IP Address
 Static IP Address
 PPPoA/PPPoE
 Bridge Mode

PPPoE/PPPoA

Servicename: _____

Username: **user@099**

Password: ••••

Encapsulation: PPPoE LLC

Bridge Interface: Activated Deactivated

Connection Setting



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il



VPI : 8
VCI : 48
ATM QoS UBR .
ISP: PPPoA / PPPoE

Then Fill In Your **Username** And **Password**.

Connection Setting	Bridge Interface : <input type="radio"/> Activated <input checked="" type="radio"/> Deactivated
	Connection : <input checked="" type="radio"/> Always On (Recommended) <input type="radio"/> Connect On-Demand (Close if idle for <input type="text" value="0"/> minutes) <input type="radio"/> Connect Manually
IP Address	TCP MSS Option : TCP MSS(default:1400) <input type="text" value="1400"/> bytes
	Get IP Address : <input type="radio"/> Static <input checked="" type="radio"/> Dynamic
	Static IP Address : <input type="text" value="0.0.0.0"/>
	IP Subnet Mask : <input type="text" value="0.0.0.0"/>
	Gateway : <input type="text" value="0.0.0.0"/>
	NAT : Enable ▾
	Default Route : <input checked="" type="radio"/> Yes <input type="radio"/> No
	TCP MTU Option : TCP MTU(default:1480) <input type="text" value="1480"/> bytes
Dynamic Route : RP2-B ▾ Direction : Both ▾	
Multicast : Disabled ▾	
<input type="button" value="SAVE"/> <input type="button" value="DELETE"/>	



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il