

Kasda-KW5212



Kasda



حضرة الزبون الكريم حتى يتم اعداد جهاز الراوتر خاصتكم يجب اتباع الخطوات التالية :

اولا يتطلب توصيل جهاز الراوتر بواسطة كابل شبكة يتم توصيلة من خلال مخرج الشبكة في الجهاز الي مخرج الشبكة بالحاسوب الخاص بكم .

ثانيا : التاكيد انه قد تم الاتصال بين الراوتر والحاسوب بنجاح

ثالثا : فتح مستعرض الانترنت لديكم ان كان الانترنت اكسلورير او جوجول كرومي

رابعا : طباعة العنوان الخاص بالراوتر وضغط على انتر

192.168.1.1

خامسا : تظهر لديكم شاشة تطلب اسم مستخدم وكلمة سر الخاصة بالراوتر

Username: admin

Password: adslroot

OK بعد كتابتهم في المكان المخصص لهم يرجى الضغط على

Address



Primo Telecommunication

072-2467000 | support@099.net.il | www.099.net.il

Connect to 192.168.1.1

TD-W8961ND

User name:

Password:

Remember my password

OK Cancel

يجب اختيار من القائمة اعلى صفحة اعداد الاروتر التالي : الوصول للصفحة الرئيسية الرجاء اختيار wizard setup ومن ثم تطبيق Apply



Please select Wizard or Advanced mode

The Wizard setup walks you through the most common configuration settings. We suggest you use this mode if it is the first time you are setting up your router or if you need to make basic configuration changes.

Use Advanced mode if you need access to more advanced features not included in Wizard mode.

Go to Wizard setup

Go to Advanced setup

Click here to always start with the Advanced setup.

Apply

Exit



Internet Configuration

ISP Parameters for Internet Access

Please verify the following settings with your Internet Service Provider (ISP). Your ISP may have given you a welcome letter or a letter including this information.

Layer2 Interface Type:

Select the Layer2 Interface Type used by your ISP. Select ADSL will use ATM mode, Select VDSL will use PTM mode.

ADSL/VDSL over PTM

WAN service type:

Select the WAN service type used by your ISP.

PPPoE

Please enter the User Name and Password.

PPP Username:

username@099 اسم المستخدم

PPP Password:

password كلمة السر

user@099

.....

Continue to Wireless Setup

Note:

Device is automatically configured to obtain an IP address automatically. The ISP will assign you a different one each time you connect to the Internet.

Yes

No

<Back

Next >

Exit

ومن ثم الضغط على التالي

NEXT

إذا بالطريقة الموضحة اعلاه يتم الاتصال بالانترنت

اعدادات الشبكة الاسلكية :

حتى يتم وحماية شبكتكم بواسطة كلمة سر يجب اختيار من القائمة الرئيسية - wireless

ومن ثم في هذه الصفحة يمكنكم اختيار اسم الشبكة خاصتكم في مكان يسمى ب SSID يمكنكم وضع الاسم الذي تريدون وفي نفس الصفحة يمكنكم ايضا وضع كلمة سر حتى تحمي الشبكة خاصتكم ومن ثم الضغط على تطبيق Apply



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il



Welcome to the Web-UI X
192.168.1.1



Wireless LAN

Wireless Parameters for Lan Access

Enable Wireless

Network Name(SSID)

Give your network a name. You will search for this name from your wireless clients.

099 Primo

اسم الشبكة

Channel Selection:

Your router can use one of several channels. You should use the default channel unless other wireless networks nearby use the same channel.

Auto

Encryption:

Use this option if you would prefer to create your own key, WPA2-PSK is stronger than WEP but not all devices are compatible with WPA2-PSK.

Manually assign a WPA2-PSK key

Pre-Shared Key

WPA2-PSK Encryption: WPA Key should be between 8 and 63 ASCII characters or 64 hexadecimal digits.

0722467000

(example: 1234567890)

كلمة السر

<Back

Next >

Exit

Welcome to the Web-UI X
192.168.1.1



CONGRATULATIONS

The Internet/Wireless Setup configuration is complete. Here are your current settings.

Internet Settings

Layer2 Interface Type:
WAN service type:
PPP Username:
PPP Password:

ADSL/VDSL over PTM
PPPoE
user@099
admin

Wireless LAN Settings

Network Name(SSID):
Channel Selection:
Encryption:
Network Key(WPA/WEP Key):

099 Primo
Auto
Manually assign a WPA2-PSK key
0722467000

Press "Apply/Save" button to finish this wizard configuration , or give up the config and click the following link to open other pages.

- Return to Wizard Main Page
- Go to Advanced Setup Page

<Back

Apply/Save

حفظ الإعدادات

بهذه الطريقة يتم حماية الشبكة بكلمة مرور خاصة بكم



Primo Telecommunication

072-2467000 | support@099.net.il | www.099.net.il



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il