

TP Link TD-W8961N



על מנת להגדיר את הנתב שלכם בצורה הנכונה ומוצלחת יש לבצע את השלבים הבאים :

שלב 1 : יש לוודא שכל החיבורים(חיבור קווי מנקודת בזק לנתב, חיבור קווי מנתב למחשב או חיבור אלחוטי) מחוברים כמו שצריך .

שלב 2 : יש לפתוח דפדפן ולהקליד את הכתובת הבאה ולהקיש כניסה ENTER



192.168.1.1

שלב 3 : יופיע על המסך חלון ידרוש שם משתמש וסיסמה

Username: admin

Password: admin

ללחוץ על כניסה OK

Address

Connect to 192.168.1.1

TD-W8961ND

User name: admin

Password:

Remember my password

OK Cancel

בחלון הבא יש תפריט עיליון יש לבחור מהרשימה את האפשרות interface setup ואז לבחור internet



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il



TP-LINK®

Wireless N ADSL2+ Modem Router

Interface | Quick Start | **Interface Setup** | Advanced Setup | Access Management | Maintenance | Status | Help

Internet | LAN | **Wireless**

Virtual Circuit : PVC2 | PVCs Summary

Status : Activated Deactivated

VPI : 0 (range: 0~255)

VCI : 35 (range: 1~65535)

QoS

ATM QoS : UBR

PCR : 0 cells/second

SCR : 0 cells/second

MBS : 0 cells

Encapsulation

ISP : Dynamic IP Address Static IP Address PPPoA/PPPoE Bridge Mode

PPPoE/PPPoA

Servicename : dataone

Username : ct3326311326

Password :

Encapsulation : PPPoE LLC

Bridge Interface : Activated Deactivated

Connection Setting

Connection : Always On (Recommended) Connect On-Demand (Close if idle for 0 minutes) Connect Manually

TCP MSS Option : TCP MSS(default:1400) 1400 bytes

IP Address

Get IP Address : Static Dynamic

Static IP Address : 0.0.0.0

IP Subnet Mask : 0.0.0.0

Gateway : 0.0.0.0

NAT : Enable

Default Route : Yes No

TCP MTU Option : TCP MTU(default:1480) 1480 bytes

Dynamic Route : RIP1 Direction : Both

Multicast : IGMP v1

MAC Spoofing : Enabled Disabled

00:00:00:00:00:00

SAVE

להחליף את VPI ל 8

להחליף את VCI ל 48

שם משתמש username@099

סיסמה password

לשמור את הנתונים

כדי לשמור את הנתונים צרייך ללחוץ על

Apply/Save



Primo Telecommunication

072-2467000 | support@099.net.il | www.099.net.il



כעת הנתב שלכם מוגדר בהצלחה

הגדרות רשת אלחוטית :

כדי להגן על רשת שלכם נא לבחור את האפשרות - wireless



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il



Access Point Settings

Access Point: Activated Deactivated

Channel: UNITED STATES Auto Current Channel: 10

Transmit Power: High

Beacon Interval(ms): 100 (range: 20~1000)

RTS/CTS Threshold: 2347 (range: 1500~2347)

Fragmentation Threshold (bytes): 2346 (range: 256~2346, even numbers only)

DTIM(ms): 1 (range: 1~255)

Wireless Mode: 802.11b+g+n

11n Settings

Channel Bandwidth: 20/40 MHz

Extension Channel: above the control channel

Guard Interval: AUTO

MCS: AUTO

Multiple SSIDs Settings

SSID Index: 1

Broadcast SSID: Yes No

Use WPS: Yes No

WPS Settings

WPS state: Unconfigured

WPS mode: PIN code PBC

WPS progress: Idle

SSID: TP-LINK_012345

Authentication Type: Disabled

להחליף Enabled

שם הרשת

WDS Settings

WDS Mode: On Off

Mac Address #1: 00:00:00:00:00:00

Mac Address #2: 00:00:00:00:00:00

Mac Address #3: 00:00:00:00:00:00

Mac Address #4: 00:00:00:00:00:00

Wireless MAC Address Filter

Active: Activated Deactivated

Action: Allow Association the follow Wireless LAN station(s) association.

Mac Address #1: 00:00:00:00:00:00

Mac Address #2: 00:00:00:00:00:00

Mac Address #3: 00:00:00:00:00:00

Mac Address #4: 00:00:00:00:00:00

Mac Address #5: 00:00:00:00:00:00

Mac Address #6: 00:00:00:00:00:00

Mac Address #7: 00:00:00:00:00:00

Mac Address #8: 00:00:00:00:00:00





יש את SSID אפשר לכתוב שם הרשת שלכם שאתם רוצים והסיסמה גם שאתם רוצים ואז ללחוץ על Apply

Multiple SSIDs Settings	SSID Index: 1 Broadcast SSID: <input checked="" type="radio"/> Yes <input type="radio"/> No Use QSS: <input type="radio"/> Yes <input checked="" type="radio"/> No SSID: TP-LINK_012345 Authentication Type: WPA-PSK	שם משתמש
WPA-PSK	Encryption: TKIP/AES Pre-Shared Key: (8-63 ASCII characters or 64 hexadecimal characters)	סיסמה
WDS Settings		

כך הנתב שלכם והרשת האלחוטית שלכם מוגדרים בהצלחה



Primo Telecommunication

072-2467000 | support@099.net.i | www.099.net.il